

INOmini 673

FM/RDS Monitor Receiver



The INOmini 673 is Inovonics' second-generation, small form-factor FM broadcast monitor for professional applications. A sensitive and selective off-air receiver for standard analog-FM broadcasts, it has application as a 'confidence monitor' or as a rebroadcast receiver in FM translator service. The 673 decodes and displays the most important data from RDS/RBDS data groups as well.

The INOmini 673 gives front-panel and remote alarm indications of program and RDS transmission errors. It can also deliver a high-quality audio feed for program distribution throughout the broadcast facility with adjustable analog and AES digital audio outputs.

(optional rack adapter)



INOVONICS
BROADCAST

5805 Hwy 9, Felton CA 95018
www.inovonicsbroadcast.com

673 FM/RDS MONITOR RECEIVER



FEATURE HIGHLIGHTS

- This sensitive and selective DSP-based (SDR) receiver has extended band coverage down to 64MHz.
- Easy front-panel setup uses jog-wheel menu navigation with a large LCD display. Accurate, hi-res metering shows RF signal and audio levels; critical system menus are hidden.
- Front-panel display of most-essential RDS/RBDS information including RT+ ‘tagging’ data.
- Balanced analog and AES-digital program line outputs are available simultaneously; levels are independently adjustable.
- Front-panel red-flashing alarms and rear-panel ‘tallies’ indicate RDS Loss or PI Error, Low Signal and Audio Program Loss.
- All receiver setup parameters are held in non-volatile memory.
- When issued, free firmware updates are easily installed in the field.

SPECIFICATIONS

Tuning Range: 64MHz – 108MHz in 100kHz steps

Antenna Input: 75Ω (F)

Sensitivity/SNR:

10dBμV for 50dB monaural S/N; 35dBuV for 70dB monaural S/N

IF Bandwidth:

Auto (signal-adaptive) or manual selection of 110kHz, 84kHz, 60kHz, 40kHz

Audio Bandwidth:

15kHz or may be manually restricted in steps down to 2kHz

De-Emphasis: 75μs or 50μs selectable

Reception Modes:

Stereo, Auto-Blended Stereo (with front-panel stereo width display), Forced-Mono

RDS Fields Displayed:

AF, CT, DI, M/S, PI, PS, PTY, PTYN, RT, RT+, TA, TP, Groups Received; RDS or RBDS protocols are selectable

Program Audio Outputs:

Balanced Analog (XLR) Left and Right outputs are adjustable from –15dBu to +15dBu in 0.2dB steps.

AES Digital (XLR) output at 44.1kHz is adjustable from –30dBFS to 0dBFS in 0.2dB steps.

Headphone Jack (3.5mm TRS) has adjustable listening level.

Front-Panel Red-Flashing Alarms:

RDS: Alarm signals the loss of RDS data or an error between the received PI code and a user-programmable PI code entry.

Low Signal: Alarm and reset trigger levels are independently adjustable relative to the RF signal level display.

Audio Loss: Alarm threshold is adjustable between 0dB and –40dB, and the alarm delay interval is adjustable between OFF and 120 seconds.

Alarm “Tallies”:

Individual open-collector NPN transistor outputs to ground are programmable for logic polarity.

USB Port:

The front-panel mini-USB port allows the quick uploading of firmware updates when issued.

Power Requirement:

12VDC at 290mA; a universal 90 – 240 VAC inline switching power supply is included with the INOmini 673 receiver.

Mounting Options:

An optional rack adapter accepts up to three INOmini modules in a 1U, 19-inch rack space. The 673 also may easily be fastened to any convenient surface with two small screws.

Size and Weight:

1.6”H x 5.5”W x 5.5”D;
4 lbs. shipping weight



MADE IN USA



5805 Hwy 9, Felton CA 95018
www.inovonicsbroadcast.com
© Inovonics, Inc. March, 2019